VARIABLE-GAIN DIGITAL FILTER

BACKGROUND OF THE INVENTION

1.   Field of the Invention:

5   The present invention relates to a digital filter,

and particularly to a variable-gain digital filter, which

is a crucial technology used for such purposes as

restricting bandwidth in the field of digital communication

widely employed in mobile communication.

10   2.   Description of the Related Art:

      In a system in which a number of types of gain are

present in the same time slot such as in an IS-95 (Interim

Standard 95, a digital portable telephone system mode

standard in the U.S.) system, gain regulation (switching)

15   is conventionally carried out in a section preceding the

bandwidth restricting (digital) filter. If this

restricting is carried out in a succeeding section,

discontinuity points occur in the output and the bandwidth

restricting characteristic of the filter will no longer be

20   satisfied.

      Thus, as shown in Fig. 1, gain selector 51 and

multiplier 52 are arranged to precede digital filter 53,

and gain that is selected in gain selector 51 for data that

have undergone baseband processing is multiplied and the

25   result then applied to digital filter 53. If X bits is the

data that have undergone baseband processing and Y bits is

the number of bits of gain in this case, the input to digital filter 53 is X + Y bits if computation is carried out without any loss of accuracy, and the construction of digital filter 53 is a circuit such as shown in Fig. 2.

5   Digital filter 53 shown in Fig. 2 is provided with a selector that switches input data and a coefficient sequence n times (where n is the filter order) in one time slot. Digital filter 53 is a circuit that realizes FIR (Finite Impulse Response) filtering by time division

10   processing. The operation is equivalent to the circuit shown in Fig. 4 that lacks multiplier 16 and selector 15. As shown in the timing chart of Fig. 3, input data IN(N)-IN(N-1) undergo time division multiplexing in selector SEL13, and after being multiplied with time division

15   multiplexed coefficients k1-kn by selector SEL14, the result is integrated. Although the time division process enables the elimination of the multiplier and adder, a number (X + Y) × n bits of flip-flops are required because the number of input bits is X + Y, and this large number of

20   components raises the problem of circuit scale.

In an IS-95 system that employs CDMA (Code Division Multiple Access), symbols having different gain must be transmitted within one frame. If gain is regulated in a section following the bandwidth restricting filter in such

25   a case, discontinuity points will occur in the output and the filter will fail to satisfy the filter bandwidth

restriction characteristic as described hereinabove. Gain must therefore be regulated in a section preceding the filter.

　　As described hereinabove using the prior art example of Fig. 1, selector 51 and multiplier 52 for regulating gain are provided in a section before the filter in the prior art, and if X is the number of bits of data input and Y is the number of bits of gain, the number of bits of input of digital filter 53 will be X + Y bits. Accordingly, a number (X + Y) × n bits of FF (flip-flops) are required in digital filter 53 in the case of the prior-art example.

SUMMARY OF THE INVENTION

　　The present invention was realized in view of the above-described state of the prior art, is directed toward solving the above-described problems of the prior art, and has as an object the provision of a novel variable-gain digital filter that is capable of reducing the scale of a circuit by incorporating a gain regulation circuit, which was arranged before the filter in the prior art, within the filter.

　　According to the variable-gain digital filter for realizing the above-described object according to the present invention, in a variable-gain digital filter that includes a gain regulation circuit in a section preceding the digital filter, the gain regulation circuit being

composed of a first selector for selecting gain and a first
multiplier for multiplying the output of the first selector
with input data, the gain regulation circuit is removed
from the section preceding the filter and incorporated

5   inside the filter.

The first multiplier of the gain regulation circuit
multiplies gain signals that are outputted from the first
selector with a coefficient sequence that is switched and
outputted from a second selector for each fixed time

10   interval and outputs the result; a second multiplier that
multiplies the output of the first multiplier with input
data that are selected by a third selector that selects and
outputs from each output of a shift register; and the
output of the second multiplier is integrated and outputted

15   by an integrator.

The variable-gain digital filter according to the
present invention is constituted by: a shift register that
is composed of n (n being a positive integer) stages of
flip-flops and that both shifts input data and generates

20   delay output by each stage; a first selector for selecting
gain; a second selector for selecting a coefficient
sequence; a third selector for selecting each delay output
of the shift register; a first multiplier for multiplying
output of the first selector with output of the second

25   selector; a second multiplier for multiplying output of the
first multiplier with output of the third selector; and an

4

integrator for integrating output of the second multiplier.

Alternatively, the variable-gain digital filter according to the present invention is constituted by dividing the first, second, and third selectors and the

5   first and second multipliers into two such that two each of the first to third selectors and the first and second multipliers are used, each of the first to third selectors switching output for time interval of $(T/n) \times 2$ (where T is the duration of one time slot, and n is the filter

10   order).

[The above and other objects, features, and advantages of the present invention will become apparent from the following description based on the accompanying drawings which illustrate examples of preferred embodiments of the

15   present invention.]

BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 is a block diagram showing the portion preceding a digital filter IS-95 of the prior art.

20   Fig. 2 is a block diagram showing the configuration of a digital filter of the prior art.

Fig. 3 is a timing chart of the operation of the prior-art example shown in Fig. 2.

Fig. 4 is a block diagram showing the first

25   embodiment of a digital filter according to the present invention.

Fig. 5 is a block diagram showing the downstream transmission system of the IS-95 system in which the present invention is applied.

Fig. 6 is a timing chart of the operation of the

5   first embodiment shown in Fig. 4.

Fig. 7 is a block diagram of the second embodiment of the present invention.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

10   Details of the first embodiment of the variable-gain digital filter according to the present invention are next described with reference to the accompanying figures.

The present invention is described hereinbelow for a case in which the invention is used in the downstream

15   transmission section of an IS-95 system.

Fig. 4 is a block diagram showing the first embodiment according to the present invention.

Fig. 5 shows the block configuration of the downstream transmission system of an IS-95 system.

20   After undergoing processing in baseband processor 22 such as attachment of CRC [cyclic redundancy check], convolutional encoding, block interleaving, long-code dispersion; power control bit insertion, Walsh dispersion, and short-code dispersion, transmission data 21 are applied

25   to digital filter 23 for restricting the bandwidth. The output of digital filter 23 are converted to a radio

6

frequency in RF unit 24 and then transmitted to the outside by an antenna.

Fig. 4 shows the details of digital filter 23, which is the inventive portion of the present invention. The digital filter of Fig. 4 is realized by time-division processing of a FIR filter of the order n.

Referring now to Fig. 4, input data 11 (X bits) are applied to shift register 12 having n stages. In addition, coefficient sequence k1-kn (J bits) is switched for each fixed time interval by selector 14 and multiplied by multiplier 16 with a gain signal (Y bits) that is selected by selector 15. The multiplied signal (J + Y bits) is multiplied in multiplier 17 with the output (X bits) of shift register 12 that is switched every fixed time interval by selector 13, and the result is applied to integrator 18. In integrator 18, data are integrated for each fixed time interval and outputted (X + Y + J + Log2 n bits).

A simplified description of the present embodiment was presented in the foregoing explanation, and a more detailed explanation of the constitution and operation of the embodiment follows hereinbelow.

In Fig. 5, a transmission signal that has undergone processing in baseband processor 22 is applied to digital filter 23 as data of X bits. In digital filter 23, the X bits of input data are applied to shift register 12 of n

7

stages as shown in Fig. 4.

Here, if IN(N) is the input data and IN(N-1) is input
data that have been delayed one time slot, the output data
of shift register 12 will be IN(N), IN(N-1), IN(N-2), ...
IN(N-n). Selector 13 switches and outputs IN(N), IN(N-1),
IN(N-2), ... IN(N-n) for each time interval T/n, which is
the time interval T of one time slot divided by n.

Selector 14 similarly switches and outputs the
coefficient sequence k1, k2, ... kn for each time interval
T/n.

A normal FIR filter of the prior art is not provided
with selector SEL15 or multiplier 16, and the products k1 ·
IN(N-1), k2 · IN(N-2), ... kn · IN(N-n) are computed for each
time interval T/n by multiplier 17, and the value shown by
equation (1) is outputted for each time interval T by
integrator 18, which is reset for each time interval T (one
time slot).

$$k1 \cdot IN(N-1) + k2 \cdot IN(N-2) + \cdots\cdots + kn \cdot IN(N-n) =$$
$$Ókn \cdot IN(N-1) \qquad\qquad (1)$$

The timing chart for this case is shown in Fig. 3.

Next, regarding the case of the present invention in
which the selector SEL15 and multiplier 16 are used, a
power control bit portion is present in the transmission
data in the downstream (from base station to terminal)
traffic channel of an IS-95 system, and the transmission
power (gain) of this portion and other portion must be

8

changed.

Gain1 is the gain for power control bits and Gain2 is the gain for other portions, and selector SEL15 performs switching of them. The selected gain is multiplied with

5 coefficient sequence kn at multiplier 16, and the result is then multiplied with IN(N), IN(N-1), IN(N-2), ········ IN(N-n) at multiplier 17.

In more concrete terms, if IN(N-1), IN(N-2), IN(N-3) are the power control bits in a particular time slot and

10 the other bits (IN(N-4), IN(N-5), ········, IN(N-n)) are not the power control bits, the output of selector 15 is controlled so as to be Gain1 at only the times when the output of selector 14 is k1, k2, and k3 and to be Gain2 at all other times. The output of integrator 18 that

15 corresponds to that time slot is therefore as shown in equation 2:

$$\text{Gain1} \cdot (\text{k1} \cdot \text{IN(N-1)} + \text{k2} \cdot \text{IN(N-2)} + \text{k3} \cdot \text{IN(N-3)} +$$
$$\text{Gain2} \cdot (\text{k4} \cdot \text{IN(N-4)} + \text{········} + \text{kn} \cdot \text{IN(N-n)}) \tag{2}$$

Fig. 6 shows the timing chart for this case.

20 If the data of IN(N) are then power control bits in the next time slot, IN(N-1), IN(N-2), IN(N-3), and IN(N-4) become power control bits, the output of selector 15 is Gain1 when the output of selector 14 is k1, k2, k3, and k4 and Gain2 at all other times, and the output of integrator

25 18 that corresponds to this time slot is therefore as shown in equation 3:

$$\text{Gain1} \cdot (k1 \cdot IN(N-1) + k2 \cdot IN(N-2) + k3 \cdot IN(N-3) +$$
$$k4 \cdot IN(N-4)) + \text{Gain2} \cdot (k5 \cdot IN(N-5) + \cdots\cdots + kn \cdot IN(N-n))$$

$$(3)$$

If the data of IN(N) are not currently the power
control bits, IN(N-2), IN(N-3), IN(N-4) become the power
control bits, the output of selector 15 becomes Gain1 when
the output of selector 14 is k2, k3, and k4 and becomes
Gain2 at all other times, and the output of integrator 18
that corresponds to this time slot is as shown in equation
(4):

$$\text{Gain1} \cdot (k2 \cdot IN(N-2) + k3 \cdot IN(N-3) + k4 \cdot IN(N-4) +$$
$$\text{Gain2} \cdot (k1 \cdot IN(N-1) + k5 \cdot IN(N-5) + \cdots\cdots + kn \cdot IN(N-n))$$

$$(4)$$

Thus, data for which gain has been regulated and
bandwidth restricted in digital filter 23 are converted to
a radio frequency in RF unit 24 and transmitted by an
antenna.

We refer to Fig. 7, in which is shown a block
configuration of the second embodiment according to the
present invention, and the second embodiment according to
the present invention is next described with reference to
the figure.

Fig. 7 shows a case in which two circuits are
employed for each of selectors SEL13, 14, and 15 and
multipliers 16 and 17 in Fig. 4 wherein each of the
selectors switches output for each time interval (T/n) $\times$ 2

10

(where T is the duration of one time slot and n is the filter order).

In other words, each of the elements of Fig. 4 is constituted by two elements, selector 13 of Fig. 4 being constituted by selectors 13a and 13b, selector 14 by selectors 14a and 14b, selector 15 by selectors 15a and 15b, multiplier 16 by multipliers 16a and 16b, and multiplier 17 by multipliers 17a and 17b.

The output timing of the integrator is unchanged from that of Fig. 4, but the multiplication performed to arrive at this result takes twice as much time and is performed by twice as many circuits.

Although the scale of the circuit in the embodiment shown in Fig. 7 is obviously greater than the configuration of Fig. 4, the embodiment is effective when n is high and the operating speed is not sufficient. The embodiment is also effective to improve the processing speed of the digital filter.

Similarly, an embodiment can be considered as yet another embodiment in which a multiplier operating speed of 1/m is realized with m times the circuit scale, and also effective for improve the processing speed of the diital filter.

The present invention is constructed and operates as described hereinabove and has as its effect the reduction of circuit scale.

In other words, in this invention, circuit scale is reduced by incorporating gain selector 51 and multiplier 52 in the prior-art example of Fig. 1 into the digital filter (15 and 16 in Fig. Fig. 4). Specifically, in a case in

5   which X is the number of data bits after baseband processing, Y is the number of gain bits, J is the number of bits of the filter coefficient sequence, and n is the order of the filter, the necessary circuit scale in the prior-art method (Fig. 1 and Fig. 2) and in the method of

10 this invention (the present invention) (Fig. 4) are as shown in Table 1:

Table 1

	FF (flip-flops)	Multiplier	Integrator
Prior-art Method	X+Y bits: n units	X bits × Y bits: 1 unit X+Y bits × J bits: 1 unit	X+Y+J bit input X+Y+J+log2n bit output
Method of Present Invention	X bits: n units	J bits × Y bits: 1 unit J+Y bits × X bits: 1 unit	X+Y+J bit input X+Y+J+log2n bit output

A comparison of the circuit scale shows that the

15 methods are equivalent regarding the integrator, but regarding the multipliers, if X+Y bits × J bits and J+Y bits × X bits are considered equivalent, the method of the present invention has smaller circuit scale when X > J, and the prior art method has smaller circuit scale when J > X.

12

In either case, however, the method of the present invention has (Y × n bits) fewer flip-flops. Accordingly, the present invention affords a large reduction in circuit scale, except in a special case when J >> X in which the

5   degree of improvement of flip-flops FF surpasses the degree of deterioration of multipliers.

The degree of improvement of flip-flops is high and the effect of the invention is particularly great in cases in which the number of bits of gain Y or the order n of the

10   filter is high.

While preferred embodiments of the present invention have been described using specific terms, such description is for illustrative purposes only, and it is to be understood that changes and variations may be made without

15   departing from the spirit or scope of the following claims.

13